

QuickQ 30+



Product Code: CS100735

QuickQ 30 is part of the ChamSys QuickQ range of user friendly and affordable lighting control consoles. The QuickQ 30 is the perfect choice of console for control of dimmer, LED colour mixing and moving light fixtures, outputting four universes of control via direct DMX or six universes via Art-Net/sACN. The console features a large 11.6 inch touch screen utilising a smart phone like interface for setup, programming and playback of your show.

Overview:

- 6 Universe output via Art-Net/sACN
- 4 RDM Enabled DMX Outputs
- User Interface Modelled on smartphone icon interfaces for ease of use
- In-Built Wi-Fi for easy connection to the remote app on iOS & Android devices
- Intuitive interface allowing simple control of all fixture attributes
- Dual Network ports allowing separation of Lighting and Control Data

Specifications:

Hardware Specifications:

- Universes supported: 6
- Direct DMX Outputs 5-Pin XLR: 4
- Master Playback Faders: 10
- Multifunction Fixture Faders: 40
- Bump Buttons: Yes
- Attribute Encoders: 4
- Multifunction Encoders: 2 (Colour/Intensity control options)
- Inbuilt 11.6" Multi-touch Display: Yes
- External Monitor: 1920 x 1080 HDMI
- Inbuilt Wi-Fi: Yes
- Network Ports: 2
- USB Ports: 2
- Audio Input: 1
- Audio Output: 1
- MIDI Ports in/out: Yes
- Max Power Consumption (mains): 60w

Software Specifications:

- Max Number of DMX Channels: 3072
- Max Number of Fixtures Supported: 3072
- Max Number of Cue Stacks: 5000
- Max Number of Chases: 5000
- Midi & Midi Timecode Supported: Yes
- OSC Supported: Yes
- RDM Autopatch for fast show patching
- Fixture library of over 60,000 fixture files
- Built in FX generator
- Colour picker and Gel inbuilt Gel library
- Offline designer software available for Windows and Mac

Included Accessories:

- Included Accessories:
- USB Desk light: 1
- Dust cover: 1
- Tablet stand: 1
- 12V power supply: 1
- IEC power cable: 1