

QuickQ 10+



Product Code: CS100715

QuickQ 10+ is part of the ChamSys QuickQ range of user friendly and affordable lighting control consoles. The QuickQ 10+ is the perfect choice of console for control of dimmer and LED colour mixing fixtures, outputting a full universe of control via direct DMX or Art-Net/sACN. The console features a large 11.6 inch touch screen utilising a smart phone like interface for setup, programming and playback of your show.

Overview:

- 1 Universe output via direct DMX or Art-Net/sACN
- User Interface Modelled on smartphone icon interfaces for ease of use
- In-Built Wi-Fi for easy connection to the remote app on iOS & Android devices
- Intuitive interface allowing simple control of all fixture attributes
- Dual Network ports allowing separation of Lighting and Control Data

Specifications:

Hardware Specifications:

- Universes supported: 1
- Direct DMX Outputs 5-Pin XLR: 1

- Master Playback Faders: 2 Chase, 1 Cue Stack
- Multifunction Fixture Faders: 20
- Bump Buttons: Yes
- Attribute Encoders: 0
- Multifunction Encoders: 2 (Colour/Intensity control options)
- Inbuilt 11.6" Multi-touch Display: Yes
- External Monitor: 1920 x 1080 HDMI
- Inbuilt Wi-Fi: Yes
- Network Port: 2
- USB Ports: 2
- Audio Input: 1
- Audio Output: 1
- MIDI Ports in/out: No
- Max Power Consumption (mains): 60w

Software Specifications:

- Max Number of DMX Channels: 512
- Max Number of Fixtures Supported: 512
- Max Number of Cue Stacks: 1
- Max Number of Chases: 2
- Midi & Midi Timecode Supported: No
- OSC Supported: Yes
- RDM Autopatch for fast show patching
- Fixture library of over 60,000 fixture files
- Built in FX generator
- Colour picker and Gel inbuilt Gel library
- Offline designer software available for Windows and Mac

Included Accessories:

- USB Desk light: 1
- Dust cover: 1
- Tablet stand: 1
- 12V power supply: 1
- IEC power cable: 1
-

Boxed Weights and Dimensions:

- Width: 680 mm (26.8 inches)
- Depth: 420 mm (16.5 inches)
- Height: 230 mm (9 inches)
- Weight: 8kg (17.63 lb)