

QuickQ Rack+



Product Code: CS100703

QuickQ Rack+ is a small rack mountable version of the QuickQ console designed for installations. It features the same operating system as QuickQ series consoles, but is designed to operate as a remote system without physical user control.

Overview

- 6 Universe output via Art-Net/sACN
- 2 RDM-Enabled DMX Outputs
- User Interface Modelled on smartphone icon interfaces for ease of use
- In-Built Wi-Fi for easy connection to the remote app on iOS & Android devices
- Intuitive interface allowing simple control of all fixture attributes
- Dual Network ports allowing separation of Lighting and Control Data

Specifications Overview

Hardware Specifications

- Universes supported: 6
- Direct DMX Outputs (5 pin DMX): 2
- 10Scene Buttons: 10
- 10Scene Ports: 4
- External Monitor: 1920 x 1080 HDMI
- Inbuilt Wi-Fi: Yes
- Network Port: 2
- USB Ports: 2
- Audio Input: 1
- Audio Output: 1
- MIDI Ports in/out: Yes
- Power Input: TrueCon Power Input: 90-250v AC
- Max Power Consumption (mains): 60w

Software Specifications

- Max Number of DMX Channels: 3072
- Max Number of Fixtures Supported: 3072
- Max Number of Cue Stacks: 2000
- Max Number of Chases: 2000
- Max Number of 10Scene Zones: 10
- OSC Supported: Yes
- RDM Autopatch for fast show patching
- Fixture library of over 60,000 fixture files
- Built in FX generator
- Colour picker and Gel inbuilt Gel library
- Offline designer software available for Windows and Mac
- Simple Hot-Takeover mode allowing an external console to take control

Included Accessories

- Rack Mount Ears: 2
- 10Scene Connectors: 4
- True1 PowerCon Cable: 1

Boxed Weights and Dimensions

- Width: 480mm (18.9 inches)
- Depth: 330mm (13.0 inches)
- Height: 150mm (5.9 inches)
- Weight: 4kg (8.81 lb)

Unit Weights and Dimensions

- Width (without ears): 403mm (15.8 inches)
- Depth: 195mm (7.7 inches)
- Height: 45mm (1.8 inches)
- Weight: 3.1kg (6.8 lb)